



### **Overview**

- This UL Recognized power supply/charger converts a 28VAC / 200VA input into single 12VDC or 24VDC non-power limited output.

### **Specifications**

- |  |  |
|--|--|
| <ul style="list-style-type: none"> <li>• 12VDC or 24VDC selectable operation.</li> <li>• 6 amp supply current.</li> <li>• Non-power limited output.</li> <li>• Input rated @ 28VAC / 200VA.</li> <li>• Filtered and electronically regulated outputs.</li> <li>• Short circuit and thermal overload protection.</li> <li>• Built-in charger for sealed lead acid or gel type batteries.</li> </ul> | <ul style="list-style-type: none"> <li>• Switching Power Supply/Charger.</li> <li>• Maximum charge current @ .7 amp.</li> <li>• Automatic switch over to stand-by battery when AC fails (zero voltage drop).</li> <li>• AC fail supervision (form "C" contacts).</li> <li>• Low battery supervision (form "C" contacts).</li> <li>• Battery presence supervision (form "C" contacts).</li> <li>• AC input and DC output LED indicators.</li> </ul> |
|--|--|

### **Agency Approvals**



UL Recognized component for Access Control System Units (UL 294)  
 Power Supplies for use with Burglar-Alarm Systems (UL 603)  
 Standard for Safety for Fire Protective Signaling Systems (UL 1481).

### **Board Dimensions (approximate):**

AL600ULB: 4.3"W x 7.1"L x 2.3"H

