

# 5865-3 and 5865-4 Installation Instructions

The following instruction are a quick reference guide, refer to the control panel installation manual *IntelliKnight 5820 Analog/Addressable Fire System* P/N 150972 for detail system information.

## Wiring the 5865-3 or 5865-4

**Note:** Installation and wiring of these devices must be done in accordance with NFPA 72 and local ordinances.

Terminate the wiring as shown in Figure 1. See also Table 1.

**Table 1: Wire Connections** 

5865-3 & 5865-4 Terminals	5820 Terminals	
	Number	Label
В	16	В
A	17	A
S+	18	+
S-	19	-

#### **Specifications**

Table 2 lists the operating specifications for the 5865-3 and 5865-4.

Table 2: 5865-3 and 5865-4 Specifications

Specifications		
Max. Line Resistance	50Ω	
Max. Alarm Current	145 mA	
Standby Current	35 mA	
Max. Voltage	24 VDC	
Operating Temperature	0° to 49° C (32° to 120° F)	
Indoor Use Only		




Figure 1: 5865-3 or 5864-4 Connection to the 5820

#### **Setting the Device Address**

The range of valid addresses is 1 -31 (0 is an invalid address). Refer to Figure 2 to set the dip switches to the desired address.




Figure 2: Setting the Device Address

### Mounting the 5865-3

The 5865-3 mounts into a standard 3-gang electrical box.

Follow these steps to mount the 5864-3:

1. Make sure that the 5865-3 is properly wired to the control panel. See Figure 1.

2. Place the 5865-3 into the 3-gang electrical box. See Figure 3.




Figure 3: 5865-3 Mounting

- 3. Place cover plate over the top of the 5865-3 and align the holes. See Figure 3.
- 4. Insert the six cover plate screws into six screw holes on the 3-gang electrical box.
- 5. Screw the six cover plate screws all the way in until the cover plate fits firmly against the 5865-3 and the electrical box. Do Not over tighten.

#### Mounting the 5865-4

The 5865-4 mounts into a standard 4-gang electrical box.

Use the same procedure as used for mounting the 5865-3.

Note: The 5865-4 uses 8 cover plate screws.



7550 Meridian Circle Maple Grove, MN 55369-4927 612-493-6455 800-328-0103 Fax: 612-493-6475

© 1997 Silent Knight

o 1997 Shent Hingh

P/N 151088, Rev A, 11/97