

# **2GIG Rely Security System**

# DIY INSTALLED SECURITY SOLD & MONITORED BY DEALERS

Affordable security that is easy to install, enabling lower cost monitoring with short term or no contract

# **Overview**

The 2GIG<sup>®</sup> Rely<sup>™</sup> is the industry's most aesthetically pleasing and smallest, self-contained security system with multiple professional monitoring options intended to be sold through dealers, who can install as usual, or sell them as a Do-It-Yourself install product. The console can be wall-mounted or placed on a counter or desk with the included desk mount, and is powered by a power supply with battery backup.

Installation of the console is as simple as plugging in the panel, which automatically syncs to the back-end. Sensors can be pre-learned by the Dealer or can be associated by the end-user, using a simple scan and add process through the 2GIG Rely App.



# Panel Shown Actual Size

Ordering Information	
----------------------	--

2GIG-RELY-KIT1	2GIG Rely 3, 1, 1 Kit –	Sack-End Back-End
2GIG-RELY-KIT2	2GIG Rely 3, 1, 1 Kit –	SECURENET Back-End

#### 2GIG Rely kits include:

Description	Qty.
2GIG Rely Panel, Cell Radio, Plug-In Power Supply, Desk Mount	1
2GIG-DW10-345 Standard Wireless Door/Window Sensor	3
2GIG-PIR1-345 Wireless Motion Detector	1
2GIG-KEY2-345 Wireless Keychain Remote	1

# **Features**

- 2 line, full-text LCD backlit display
- 16 security zones
- 8 users
- 8 Keychain remotes (Do not reduce zone count)
- Integrated 345 MHz wireless transceiver works with many existing 2GIG sensors
- Internal cellular radio for communication
- Includes a piezo sounder for:
  - Alarm siren
  - Voice or tone chimes
  - System status notifications
  - Keypad presses
- LCD screen and backlit buttons offer adjustable brightness



#### Easy to Program & Install

2GIG<sup>®</sup> Rely<sup>™</sup> is designed to be easy to install using a process that walks customers step-by-step through the installation, programming and testing of their security system using the Rely smart phone or tablet app included with each monitored system, available for both iOS<sup>™</sup> and Android<sup>™</sup> devices. This process includes in-app installation videos featuring best practices for each specific sensor and installation site.

#### Reduces Key Costs for Security Dealers

Competitive solutions sold direct to consumers that offer low cost monitoring, with short or no contract terms have impacted many Security Dealers. 2GIG worked with Dealers to develop Rely to be an affordable product family, enabling Dealers to sell the equipment up front. By eliminating the installation costs, Dealers will be able to offer lower monthly monitoring costs with shorter contracts or even month-to-month, no contract monitoring.

# **Specifications**

Device in put	100 2/0//40 50 /011-
Power input	100-240 VAC, 50-60 Hz
Power output	5V, 1.5A, 7.5W max
Peak current	1.7A
Cellular network	3G GSM AT&T Radio
Operating temperature	32° to 120°F (0° to 49° C)
Storage temperature	-30° to 140°F (-34° to 60° C)
Max. relative humidity	90% non-condensing
Dimensions	(H x W x D) 3.8" x 5.2" x 0.9"

#### Easy to Use 2GIG Rely App

Every monitored 2GIG Rely system uses the Rely App to control the system. The app requires a PIN or Touch ID for secure use and allows users to disarm or arm their system to stay or away modes. The Rely App also enables the user to configure and set-up notifications to provide status updates or alerts.

#### Secure Cellular Communication

The integrated cellular radio communicates with the Alarm Monitoring Center, as well as your 2GIG Rely App to protect your family, home and assets without the need of a traditional phone line.

#### A System that Moves and Grows with the User

Dealers drove us to create a product that more people could afford for both equipment and monitoring. 2GIG Rely is a solution that makes a security system possible for more people than ever. The system is robust enough to add more sensors and move with you from home to home.

# Panel

2 x 20 LCD Backlit Screen Away and Stay Quick Arming Buttons Time and date display Integrated Piezo Sounder Firmware updates: Over-the-air

### Certifications



# Compatible Sensors



Wireless Door / Window Sensor 2GIG-DW10-345



Wireless Smoke/ Heat/ Freeze Detector 2GIG-SMKT3-345



Wireless Recessed Door / Window Sensor 2GIG-DW20R-345



Wireless Glass Break Detector 2GIG-GB1-345





Wireless Carbon Monoxide Detector 2GIG-C03-345



Wireless PIR Motion Detector 2GIG-PIR1-345



Wireless Keychain Remote 2GIG-KEY2-345



© 2017 Nortek Security & Control LLC. All Rights Reserved P/N 10016222A

1950 Camino Vida Roble, Suite 150 • Carlsbad CA 92008 • 760.438.7000 • 760.800.421.1587 nortekcontrol.com