



# FireFighter™ Smoke Detector 345 MHz Sensor/Transmitter

Model #: 2GIG-FF-345

## Features

- Monitors any existing UL listed smoke detector
- Does not impact UL or Fire Marshall approval of existing smoke detectors
- 100% compatible with 2GIG panels and Honeywell 5800 receivers
- Uses one CR123A long life lithium battery
- FCC, IC, and ETL listed in US and Canada to UL985 standard



The 2GIG FireFighter is a quick and easy way to add smoke alarm monitoring to your 2GIG (or 345 MHz Honeywell) control panel. FireFighter is specifically tuned to recognize the specific cadence of a UL listed smoke detector's alarm. This unique audio technology monitors existing UL listed smoke detectors in a home and will send a wireless signal to the control panel when an alarm is detected. The control panel will then contact the connected central monitoring station.

When used with the interconnected smoke detectors, found in most homes today, FireFighter adds a new level of alerts by monitoring all the smoke detectors in the home from a single device

## Package Contents

- FireFighter Smoke Detector Sensor
- CR2032 battery
- Mounting package included

## Compatible Alarm Systems

- 2GIG GC2 and GC3 Control Panels
- Honeywell 5800 Receivers/Panels

\* This product has been tested and verified to operate with the above alarm panel systems. Other brand/model 345 MHz alarm systems may also work with this product.



2GIG is a registered trademark of Nortek Security & Control, LLC. Honeywell, the Honeywell logo, and all product names appearing herein are trademarks and/or service marks owned by Honeywell International Inc

## Specifications

Wireless Protocol/Freq.	2GIG & Honeywell / 345 MHz
Detection Distance	6 inches maximum
Backup Battery (included)	CR123 or equivalent Lithium battery
Backup Battery Life	5 years
Operating Temperature	32°-120° F (0° - 49° C)
Supervisory Interval	64 minutes
Relative Humidity	5-95% RH, non-condensing
Weight	8.57 oz. (243g)
Certification	FCC, IC, ETL in USA and Canada to UL 985 standard

Model	Order PN	Compatible Alarm Panels
2GIG-FF-345	2GIG-FF-345	2GIG Alarm Panel, Honeywell 5800 Wireless Alarm Panels

