DTK-4LVLPCR, DTK-3LVLPX

Card Reader Surge Protection





various types of card readers. The 4LVLPCR protects power, data and LED circuits in one compact package; the 3LVLPX is designed to protect Wiegand and Wiegand-type 12 Volt, three-pair card reader systems.

DITEK's DTK-4LVLPCR and 3LVLPX are designed to protect

Product Features

- Series connection, parallel function adds no resistance to loop circuits
- Protect 3 or 4 pairs of power/data connections
- Protect power, LED and data lines (4LVLPCR)
- Single ground point for all protected circuits


Selection Guide:

- DTK-4LVLPCR: Card Reader Protection (12V Power, 24V Power)
- DTK-3LVLPX: Wiegand-Type Card Reader Protection (3 pairs, 12-14V)

Accessories

DIN Rail Kit – Part Number DTK-DRK

DTK-4LVLPCR Wiring Diagram



Technical Specifications			
Part Number:	DTK-4LVLPCR	DTK-3LVLPX	
Service Voltage Power:	12V/24V	12V	
Service Voltage Data:	<5V	12V	
Service Voltage LED:	<5V	N/A	
MCOV Power:	18V/38V	18V	
MCOV Data:	6.8V	18V	
MCOV LED:	8V	N/A	
Clamping Voltage Power:	22V/47V	22V	
Clamping Voltage Data:	7.2V	22V	
Clamping Voltage LED:	12V	N/A	
Protection Modes:	Line-Ground (All)	Line-Ground (All)	
Surge Current Rating:	(Power) 2,000 Amps/pair (Data/LED) 500 Amps/pair	2,000 Amps/pair	
Max Continuous Current:	3 Amps Power/Data 150mA LED	3 Amps	

Mechanical Characteristics

Connection Method:	#22-#16 AWG screw terminals		
Housing:	ABS		
Operating Temperature:	-40°F - 158°F (-40°C - 70°C)		
Maximum Humidity:	95% non-condensing		
Dimensions:	3.0"L x 1.6"W x 1.6"H (76 mm x 41 mm x 41 mm)		
Weight:	4oz (113g)		

Quality, Standards & Approval

Agency Approvals:	N/A	UL497B	
Standards Compliance:	ABS		
Warranty:	Ten Year Limited		

Every precaution has been taken to ensure that this literature is accurate and complete. DITEK Corporation assumes no responsibility and disclaims all liability for damages resulting from the use of this information or for any errors or omissions.





